

ROMPACT 30.20 E³ Battery Powered Impact Wrench

**VARIABLE WRENCHING
WITH MINIMUM
HANDARM VIBRATION.**



ROMPACT 30.20 (Version 3.0) – 7809900006
ROBATTERY 71.01 400 Wh – 7826800002
Socket

For tightening and loosening nuts, sleeper, switch and fishplate bolts.

THE ADVANTAGES. YOUR BENEFITS.

Compact. Powerful. Robust.

- Adjustable angle design for working in tight spaces e.g. for wrenching fishplates and switches
- Version 03: Perfect for tightening and loosening switch and fishplate bolts
- Version 04: Perfect for tightening and loosening sleeper bolts with very good visibility of the socket

Ergonomic use

- Easy, ergonomic operation in any work position

- No transfer of the wrenching torque to the operator
- Version 04: Height adjustment of handles due to different extensions possible (optional accessories)
- Hand-arm vibration < 5 m/s² allows for effortless wrenching
- LED lighting

Flexible application

- 1-inch square drive to accept the corresponding sockets
- Adjustable output 50/75/100 % for maximum flexibility
- Clockwise/counter-clockwise rotation

SPECIFICATION	Version 3.0	Version 4.0
Drive	BLDC electric motor	BLDC electric motor
Output	2.0 kW	2.0 kW
Tightening/loosening torque	max. 1800 Nm	max. 1800 Nm
Angle adjustable	yes	yes
Vibration damping	yes	yes
Number of wrenching cycles		
Battery 400 Wh	300 (4 seconds each)	300 (4 seconds each)
Battery 800 Wh	550 (4 seconds each)	550 (4 seconds each)
Battery 2300 Wh	1600 (4 seconds each)	1600 (4 seconds each)
Weight		
Impact Wrench (incl. 400 Wh battery)	from 19.0 kg	from 21.0 kg
Battery 400 Wh	3.9 kg	3.9 kg
Battery 800 Wh	6.3 kg	6.3 kg
Battery 2300 Wh	16.0 kg	16.0 kg
Adapter for battery 2300 Wh	6.6 kg (incl. connecting cable)	6.6 kg (incl. connection cable)
Socket	1.5 kg	1.5 kg
Dimensions (L x W x H)	850 x 560 x 220 mm	650 x 550 x 220 mm

ACCESSORIES

7826800002 Battery 400 Wh
 7806800002 Battery 800 Wh
 7806850001 Charger for batteries 400/800 Wh

7836800001 Battery 2300 Wh
 7879900001 Charger for battery 2300 Wh
 7838930001 Adapter for using 2300 Wh battery
 7838930002 Backpack system for battery 2300 Wh



**ROMPACT 30.20 (Version 03) –
 7809900006**



**ROMPACT 30.20 (Version 04) –
 7809900011**

Sockets

Hexagonal

9871033313 AF 30
 9871033309 AF 32
 9002501223 AF 34
 9871033314 AF 35
 9871033311 AF 36
 9871033315 AF 38
 8098950100 AF 39 Special 230 mm
 9871033391 AF 39
 9871033304 AF 41
 9871033308 AF 42
 9002501224 AF 46

Rectangular

9871033317 rect. 18 x 26
 9871033302 rect. 21 x 28
 9871033305 rect. 30 x 22

Square

9871033303 SQ 19x19/17x17
 9871033318 SQ 21 x 21
 9871033306 SQ 22 x 22
 9871033319 SQ 24 x 24

Special sockets

8003062130 Combined socket
 AF 41 & rect. 21 x 28

Other sockets available on request.



Drill adapter/sleeper drill bit

Drill adapter

8099910001 SDS Plus chuck adapter

Sleeper drill bits

Max. drilling depth 150 mm with SDS Plus chuck adapter

9002501808 Ø 14 mm
 9002501809 Ø 16 mm
 9002501810 Ø 18 mm
 9002501811 Ø 20 mm
 9002501812 Ø 22 mm

Other drill bits available on request.

Miscellaneous

8003009006 Extension 180 mm/1" adapter
 8003009005 Extension 330 mm/1" adapter
 8003009007 Cardan joint 1" adapter
 9909992145 O-ring, circlip to secure socket
 9900070056 Cylindrical pin Ø 6 mm to secure socket

Adaper for tools for sleeper renovation (see ROWRENCH 30.83):

8338930003 Adapter square 24 mm to 1 inch
 8338930004 Adapter 1inch to square 24 mm